

SPECIFICATION

| | |
|---|--|
| 1.MODEL | YM-261C-9 |
| 2.TYPE | COMMUTATOR MOTOR |
| 3.DIMENSIONS | AS PER DRAWING |
| 4.NAMEPLATE RATING | |
| 1)VOLTAGE | 230V AC |
| 2)FREQUENCY | 50Hz |
| 3)CURRENT | 0.45A |
| 4)INPUT | 90W |
| 5)SPEED | 6000min ⁻¹ |
| 5.MOTOR CHARACTERISTICS | |
| 1)VOLTAGE | 230V AC,50Hz |
| 2)INPUT | 90W |
| 3)LOAD CURRENT | 0.45A±10% |
| 4)SPEED | 6000±1000R.P.M. |
| 5)OUTPUT | 38W±10% |
| 6)STARTING TORQUE | MORE THAN 156.8mN · m(1600g-cm) |
| 6.DIELECTRIC STRENGTH(Under Normal Condition) | |
| 1)BASIC INSULATION | AC 1250V FOR 1 MIN.OR AC 1400V FOR 1 SEC. |
| 2)REINFORCED INSULATION | AC 3750V FOR 1 MIN.OR AC 4200V FOR 1 SEC. |
| 3)CUTOFF CURRENT | 10mA |
| 7.INSULATION RESISTANCE(Under Normal Condition) | |
| 1)BASIC INSULATION | MORE THAN 2MΩ |
| 2)REINFORCED INSULATION | MORE THAN 7MΩ |

